
5. Exploded View and Parts List

5-1 Cabinet Assembly----- 5-2

5-2 Electrical Parts List----- 5-4

Loc. No	Parts No.	Description / Specification	Qty	SNA	Remark
C011	AK61-00137A	SPRING ETC-DOOR;DVD-R4000,COIL,PI0.	1	SA	
D001A	AK96-01294A	ASSY ENGINE P-BD DECK;BD-P6A,SEIN,1A	1	SA	
F001A	AK96-01282A	ASSY COVER P-FRONT;BD-C5300/XEF,SEF	1	SA	
FC551	3809-002551	FFC CABLE-FLAT;30V,80C,100mm,22P,1.	1	SA	
FC552	3809-002552	FFC CABLE-FLAT;30V,80C,40mm,5P,1.0m	1	SA	
FC557	3809-002557	FFC CABLE-FLAT;30V,80C,95mm,5P,1mm,UJ2896	1	SA	
FD03	AK64-02438A	DOOR-TRAY;BD-C5300/XAA,PMMA + ABS H	1	SA	
FD12	AK64-02427A	DOOR-USB;BD-C5500/XAA,ABS BLK + ELA	1	SA	
M0014	AK94-00328A	ASSY PCB MAIN;BD-C5300/XEF,MAIN PCB	1	SA	
MR01A	AK94-00285B	ASSY PCB FRONT-BD-C5300;BD-C5300,AS	1	SA	
P001A	AK94-00324B	ASSY PCB SMPS;BD-C5500/XAX,ASSY PCB	1	SA	
PSU01	AK94-00282A	ASSY PCB S-SUB-USB;BD-C5500/XAA,ASS	1	SA	
REMO2	AK59-00104R	REMOCON-ASSY;"10 BDP BD-C5500/XAA,S	1	SA	
T001	AK63-00607B	COVER-TOP;BD-C5300/XEF,PCM,T0.45,W5	1	SA	
T0268	AC39-10019A	CBF-POWER CORD;AT,CP2,HOUIING(2P),25	1	SA	
W275	6003-001561	SCREW-TAPTYPE;BH,+,-,B,M3,L6,ZPC(WH	9	SA	
W390	6003-000276	SCREW-TAPTYPE;BH,+,-,B,M3,L10,ZPC(W	3	SA	
W391	6003-000275	SCREW-TAPTYPE;BH,+,-,B,M3,L10,ZPC(BLK	5	SA	

5-2 Electrical Parts List

Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark	Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark
M0014AK94-00328A ASSY PCB MAIN;BD-C5300/KEF,MAIN PCB						1	SA				
BD1	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MH	1	SA		C145	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA	
BD12	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MH	1	SA		C146	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,160	1	SNA	
BD14	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MH	1	SA		C147	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,160	1	SNA	
BD2	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MH	1	SA		C148	2203-002687	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,100	1	SA	
						C149	2203-002711	C-CER,CHIP;100nF,10%,25V,X7R,1608	1	SA	
BD3	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MH	1	SA		C15	2203-000254	C-CER,CHIP;10nF,10%,16V,X7R,TP,1005	1	SA	
BD6	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MH	1	SA		C150	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
BD8	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MH	1	SA		C151	2203-002687	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,100	1	SA	
BD9	3301-001404	BEAD-SMD;30ohm,2012,TP,15.9OHM/30MH	1	SA		C152	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC	
C1	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C153	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,1608	1	SNA	
C10	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C154	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC	
C100	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C155	2203-006562	C-CER,CHIP;100nF,10%,10V,X5R,TP,10	1	SNA	
C101	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C156	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA	
C102	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C157	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA	
C103	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C158	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C104	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C159	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C105	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C16	2203-000254	C-CER,CHIP;10nF,10%,16V,X7R,TP,1005	1	SA	
C106	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C160	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C107	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C161	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C108	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C162	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C109	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA		C163	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C11	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C164	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,1608	1	SNA	
C110	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,160	1	SNA		C165	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,1608	1	SNA	
C111	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C166	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,1608	1	SNA	
C112	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,160	1	SNA		C167	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,1608	1	SNA	
C113	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C168	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,1608	1	SNA	
C114	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C169	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,1608	1	SNA	
C115	2203-007176	C-CER,CHIP;1000nF,10%,16V,X5R,TP,2	1	SNA		C170	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C116	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C171	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC	
C117	2203-006562	C-CER,CHIP;100nF,10%,10V,X5R,TP,10	1	SNA		C172	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA	
C118	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C173	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA	
C119	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,160	1	SNA		C174	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA	
C12	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C175	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,160	1	SNA	
C120	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C176	2203-002687	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,100	1	SA	
C121	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA		C177	2203-002711	C-CER,CHIP;100nF,10%,25V,X7R,1608	1	SA	
C122	2203-006562	C-CER,CHIP;100nF,10%,10V,X5R,TP,10	1	SNA		C178	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA	
C123	2203-003039	C-CER,CHIP;0.008nF,0.25pF,50V,COG,T	1	SNA		C179	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA	
C124	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA		C18	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C125	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C180	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C126	2203-002711	C-CER,CHIP;100nF,10%,25V,X7R,1608	1	SA		C181	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C127	2203-000425	C-CER,CHIP;.018nF,5%,50V,COG,TP,100	1	SA		C182	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C128	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C183	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C129	2203-006474	C-CER,CHIP;2200nF,20%,6.3V,X5R,201	1	SA		C184	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA	
C13	2203-000254	C-CER,CHIP;10nF,10%,16V,X7R,TP,1005	1	SA		C185	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA	
C130	2203-006474	C-CER,CHIP;2200nF,20%,6.3V,X5R,201	1	SA		C186	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA	
C131	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C187	2203-005249	C-CER,CHIP;100nF,10%,50V,X7R,TP,160	1	SNA	
C132	2203-006474	C-CER,CHIP;2200nF,20%,6.3V,X5R,201	1	SA		C188	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA	
C133	2203-006474	C-CER,CHIP;2200nF,20%,6.3V,X5R,201	1	SA		C189	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA	
C134	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C19	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C135	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C190	2203-006047	C-CER,CHIP;33nF,10%,16V,X7R,1005	1	SA	
C136	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C191	2203-006047	C-CER,CHIP;33nF,10%,16V,X7R,1005	1	SA	
C137	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C192	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA	
C138	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C193	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA	
C139	2203-000254	C-CER,CHIP;10nF,10%,16V,X7R,TP,1005	1	SA		C194	2203-002711	C-CER,CHIP;100nF,10%,25V,X7R,1608	1	SA	
C14	2203-000254	C-CER,CHIP;10nF,10%,16V,X7R,TP,1005	1	SA		C195	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C140	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C196	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA	
C141	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C197	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA	
C142	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C198	2203-002285	C-CER,CHIP;10nF,10%,50V,X7R,1005	1	SNA	
C143	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C199	2203-002994	C-CER,CHIP;0.068nF,5%,50V,CH,BK,100	1	SNA	
C144	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA		C2	2203-000233	C-CER,CHIP;0.1nF,5%,50V,COG,TP,1005	1	SA	

Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark	Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark
C20	2203-006324	C-CER,CHIP;2200nF,10%,10V,X5R,1608	1	SA		C31	2203-006562	C-CER,CHIP;1000nF,10%,10V,X5R,TP,10	1	SNA	
C200	2203-005659	C-CER,CHIP;0.18nF,5%,50V,NP0,1005	1	SNA		C32	2203-006562	C-CER,CHIP;1000nF,10%,10V,X5R,TP,10	1	SNA	
C201	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C33	2203-006324	C-CER,CHIP;220nF,10%,10V,X5R,1608	1	SA	
C202	2203-006047	C-CER,CHIP;33nF,10%,16V,X7R,1005	1	SA		C34	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC	
C203	2203-002711	C-CER,CHIP;100nF,10%,25V,X7R,1608	1	SA		C35	2203-006324	C-CER,CHIP;2200nF,10%,10V,X5R,1608	1	SA	
C204	2203-006047	C-CER,CHIP;33nF,10%,16V,X7R,1005	1	SA		C36	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C205	2203-006047	C-CER,CHIP;33nF,10%,16V,X7R,1005	1	SA		C37	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C206	2203-006047	C-CER,CHIP;33nF,10%,16V,X7R,1005	1	SA		C38	2203-006562	C-CER,CHIP;1000nF,10%,10V,X5R,TP,10	1	SNA	
C207	2203-002711	C-CER,CHIP;100nF,10%,25V,X7R,1608	1	SA		C39	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C208	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA		C4	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,1608	1	SNA	
C209	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA		C40	2203-001397	C-CER,CHIP;2.2nF,5%,50V,NP0,1608	1	SA	
C21	2203-006324	C-CER,CHIP;2200nF,10%,10V,X5R,1608	1	SA		C41	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C210	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA		C42	2203-001397	C-CER,CHIP;2.2nF,5%,50V,NP0,1608	1	SA	
C211	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	SNA		C43	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C212	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,1608	1	SNA		C44	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C213	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C45	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C214	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C46	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C215	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C47	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C216	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C48	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C217	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA		C49	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C218	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA		C5	2203-006824	C-CER,CHIP;4700nF,10%,10V,X5R,1608	1	SNA	
C219	2203-000438	C-CER,CHIP;1nF,10%,50V,X7R,TP,1005	1	SA		C50	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C22	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C51	2203-000643	C-CER,CHIP;0.024nF,5%,50V,COG,TP,10	1	SA	
C220	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA		C52	2203-000643	C-CER,CHIP;0.024nF,5%,50V,COG,TP,10	1	SA	
C221	2203-006562	C-CER,CHIP;1000nF,10%,10V,X5R,TP,10	1	SNA		C53	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C222	2203-003039	C-CER,CHIP;0.008nF,0.25pF,50V,COG,T	1	SNA		C54	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C224	2203-006698	C-CER,CHIP;1000nF,10%,25V,X7R,1608	1	SNA		C55	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C225	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C56	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C226	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA		C57	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C227	2203-006336	C-CER,CHIP;1000nF,10%,25V,X5R,3216	1	SA		C58	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C228	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C59	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C229	2203-006361	C-CER,CHIP;1000nF,10%,10V,X5R,TP,2	1	SC		C6	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C23	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C60	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	SA	
C230	2203-000233	C-CER,CHIP;0.1nF,5%,50V,COG,TP,1005	1	SA		C61	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C231	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C62	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C232	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C63	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C233	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C64	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C234	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C65	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C235	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA		C66	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C236	2203-000233	C-CER,CHIP;0.1nF,5%,50V,COG,TP,1005	1	SA		C67	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C237	2203-000233	C-CER,CHIP;0.1nF,5%,50V,COG,TP,1005	1	SA		C68	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C238	2203-000233	C-CER,CHIP;0.1nF,5%,50V,COG,TP,1005	1	SA		C69	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C239	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA		C7	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C24	2203-006324	C-CER,CHIP;2200nF,10%,10V,X5R,1608	1	SA		C70	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C240	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA		C71	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C241	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA		C72	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C242	2203-006562	C-CER,CHIP;1000nF,10%,10V,X5R,TP,10	1	SNA		C73	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C246	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C74	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C247	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C75	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C248	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C76	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC	
C249	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C77	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C25	2203-006562	C-CER,CHIP;1000nF,10%,10V,X5R,TP,10	1	SNA		C79	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C250	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C8	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C251	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC		C80	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C252	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC		C81	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C253	2203-006361	C-CER,CHIP;10000nF,10%,10V,X5R,TP,2	1	SC		C82	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C254	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	SA		C83	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C255	2203-006336	C-CER,CHIP;10000nF,10%,25V,X5R,3216	1	SA		C84	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C257	2203-006158	C-CER,CHIP;100nF,10%,16V,X7R,1005	1	SNA		C85	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C27	2203-006324	C-CER,CHIP;2200nF,10%,10V,X5R,1608	1	SA		C86	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C28	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C87	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C29	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C88	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C3	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		C89	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA	
C30	2203-006562	C-CER,CHIP;1000nF,10%,10V,X5R,TP,10	1	SNA							

Exploded Views and Parts List

Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark	Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark
C9	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		Q13	0501-000465	TR-SMALL SIGNAL;MMBT3904,NPN,350mW,	1	SA	
C90	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		Q14	0504-000126	TR-DIGITAL;KSR1101,NPN,200mW,4.7K/4	1	SA	
C91	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		Q15	0501-000546	TR-SMALL SIGNAL;KSA1298,PNP,200mW,S	1	SNA	
						Q16	0501-000457	TR-SMALL SIGNAL;MMBT2222A/KST2222A,	1	SA	
C92	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		Q17	0501-000457	TR-SMALL SIGNAL;MMBT2222A/KST2222A,	1	SA	
C93	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA							
C94	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		Q18	0505-001344	FET-SILICON;FDN360P,P,-30V,-2A,0.08	1	SNA	
C95	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		Q19	0505-002386	FET-SILICON;AO3415AL,P,-20V,-4A,0.0	1	SA	
C96	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		Q2	0501-000457	TR-SMALL SIGNAL;MMBT2222A/KST2222A,	1	SA	
						Q20	0505-002386	FET-SILICON;AO3415AL,P,-20V,-4A,0.0	1	SA	
C97	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		Q23	0504-000126	TR-DIGITAL;KSR1101,NPN,200mW,4.7K/4	1	SA	
C98	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA							
C99	2203-006048	C-CER,CHIP;100nF,10%,10V,X7R,TP,100	1	SA		Q24	0501-000465	TR-SMALL SIGNAL;MMBT3904,NPN,350mW,	1	SA	
CN10	3708-002603	CONNECTOR-FPC/FFC/PIC;22P,1mm,SMD-S	1	SNA		Q25	0501-000465	TR-SMALL SIGNAL;MMBT3904,NPN,350mW,	1	SA	
CN12	3708-001935	CONNECTOR-FPC/FFC/PIC;40P,0.5mm,SMD	1	SNA		Q26	0505-000110	FET-SILICON;2N7002,N,60V,115mA,7.5o	1	SA	
						Q27	0504-000129	TR-DIGITAL;KSR1104,NPN,200mW,4.7K/4	1	SA	
CN14	3708-002603	CONNECTOR-FPC/FFC/PIC;22P,1mm,SMD-S	1	SNA		Q3	0501-000465	TR-SMALL SIGNAL;MMBT3904,NPN,350mW,	1	SA	
CN2	3722-003017	JACK-MODULAR;8P/8C,No,ANGLE,W/O,AU,	1	SNA							
CN3	3722-003021	JACK-PIN;6P (W/L),Ni+SN,RED/BLU/GRN	1	SNA		Q4	0504-000152	TR-DIGITAL;KSR2101,PNP,200mW,4.7K/4	1	SA	
CN4	3701-001293	CONNECTOR-HDMI;19P,2R,FEMALE,SMD-A,	1	SA		Q5	0501-000465	TR-SMALL SIGNAL;MMBT3904,NPN,350mW,	1	SA	
CN9	3710-003239	SOCKET-BOARD TO CABLE;11P,2R,1.25mm	1	SNA		Q6	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22	1	SA	
						Q7	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22	1	SA	
D1	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,	1	SNA		Q8	0501-000457	TR-SMALL SIGNAL;MMBT2222A/KST2222A,	1	SA	
D2	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,	1	SNA							
D3	0406-001239	DIODE-TVS;RClamp0502B,6/-1V,125W,S	1	SA		Q9	0504-000126	TR-DIGITAL;KSR1101,NPN,200mW,4.7K/4	1	SA	
D4	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,	1	SNA		R1	2007-000138	R-CHIP;100ohm,5%,1/16W,TP,1005	1	SNA	
D5	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,	1	SNA		R10	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SNA	
						R101	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
						R102	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SNA	
D6	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,	1	SNA							
D7	0406-001239	DIODE-TVS;RClamp0502B,6/-1V,125W,S	1	SA		R103	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
D8	0401-000008	DIODE-SWITCHING;DAN217,80V,100MA,SO	1	SA		R104	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
D9	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150mA,	1	SNA		R105	2007-000139	R-CHIP;220ohm,5%,1/16W,TP,1005	1	SNA	
HC1	2203-006170	C-CER,CHIP;220nF,10%,16V,X7R,1608	1	SNA		R106	2007-000139	R-CHIP;220ohm,5%,1/16W,TP,1005	1	SNA	
						R107	2007-000606	R-CHIP;240ohm,1%,1/10W,TP,1608	1	SA	
HP_SUB	0202-001767	SOLDER-CREAM;LST-5710,D20-38,Sn-57B	1.338	SNA		R110	2007-007318	R-CHIP;1Kohm,1%,1/16W,TP,1005	1	SNA	
HP_SUB	0202-001608	SOLDER-WIRE FLUX;LFC7-107,DO.8,99.3	0.025	SNA		R111	2007-000343	R-CHIP;120ohm,1%,1/10W,TP,1608	1	SA	
IC1	1204-003090	IC-VIDEO DECODER;BCM7630,FCBGA,422P	1	SNA		R112	2007-000606	R-CHIP;240ohm,1%,1/10W,TP,1608	1	SA	
IC10	1203-001212	IC-VOL. DETECTOR;7029,SOT-89,3P,-P	1	SA		R113	2007-000343	R-CHIP;120ohm,1%,1/10W,TP,1608	1	SA	
IC11	1201-000166	IC-OP AMP;LM358,SOP,ST,8P,150MIL,DU	1	SA		R115	2007-000242	R-CHIP;1.5Kohm,5%,1/16W,TP,1005	1	SNA	
IC12	1203-006104	IC-DC/DC CONVERTER;MP8707EN,SOIC8E,	1	SA		R119	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC16	1201-000166	IC-OP AMP;LM358,SOP,ST,8P,150MIL,DU	1	SA		R12	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	1	SA	
IC17	1105-002083	IC-DRAM;K4B1G0846E-HCH9,DDR3 1G SDR	1	SNA		R121	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC18	1001-001482	IC-ANALOG SWITCH;MAX4610CUD,SPST CM	1	SNA		R122	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC19	1003-002187	IC-MOTOR DRIVER;AM9268,SOP,42P,18x7	1	SA		R123	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC1A	AK62-00031A	HEAT SINK-ES;BD-C5500,C6500,A6063,P	1	SNA		R124	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC2	1203-005469	IC-POWER SUPERVISOR;MIC2009YM6,SOT-	1	SA		R125	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC20	1003-002188	IC-MOTOR DRIVER;AM9858,SOP,28P,18x7	1	SNA		R126	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC22	1203-002253	IC-POSI.FIXED REG.;KIA7808AF,DPAK,3	1	SA		R128	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC23	1203-006012	IC-DC/DC CONVERTER;MP8725EL,QFN14,1	1	SA		R129	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC24	1203-006067	IC-POWER SUPERVISOR;TPS2553DBVR,SOT	1	SNA		R130	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC25	1203-006104	IC-DC/DC CONVERTER;MP8707EN,SOIC8E,	1	SA		R131	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC3	1002-001581	IC-D/A CONVERTER;CS4353-CNZR,24,QFN	1	SNA		R132	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC4	1201-003013	IC-VIDEO AMP;MM1797EVBE,TSOP-16B,16	1	SNA		R135	2007-000242	R-CHIP;1.5Kohm,5%,1/16W,TP,1005	1	SNA	
IC5	AK97-04068A	ASSY MICOM-FLASH;BD-C5500/XAA,AK41-	1	SNA		R136	2007-000242	R-CHIP;1.5Kohm,5%,1/16W,TP,1005	1	SNA	
IC5	1107-001887	IC-NAND FLASH;NAND02GW3B2DN6,2Gbit,	1	SNA		R137	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC6	1105-002083	IC-DRAM;K4B1G0846E-HCH9,DDR3 1G SDR	1	SNA		R138	2007-000148	R-CHIP;10Kohm,5%,1/16W,TP,1005	1	SNA	
IC7	1105-002066	IC-DRAM;K4B1G1646E-HCH9,DDR3 SDRAM,	1	SNA		R14	2007-000143	R-CHIP;4.7Kohm,5%,1/16W,TP,1005	1	SNA	
IC8	1103-001398	IC-EEPROM;24C02,2Kbit,256Kx8,SOIC,8	1	SA		R141	2007-000162	R-CHIP;100Kohm,5%,1/16W,TP,1005	1	SNA	
IC9	AK09-00211A	IC MICOM-MASK;MC80F0448,BD-C5500/65	1	SNA		R142	2007-000157	R-CHIP;47Kohm,5%,1/16W,TP,1005	1	SNA	
L14	2703-003559	INDUCTOR-SMD;4.7uH,20%,8080	1	SNA							
L2	2703-000402	INDUCTOR-SMD;1uH,20%,3225	1	SNA		R145	2007-000140	R-CHIP;1Kohm,5%,1/16W,TP,1005	1	SNA	
L8	2703-003559	INDUCTOR-SMD;4.7uH,20%,8080	1	SNA		R146	2007-001153	R-CHIP;750ohm,1%,1/10W,TP,1608	1	SA	
L9	2703-001873	INDUCTOR-SMD;4.7uH,20%,6060	1	SA		R148	2007-000152	R-CHIP;20Kohm,5%,1/16W,TP,1005	1	SNA	
OP1	3707-001094	CONNECTOR-OPTICAL;ANGLE-TX	1	SA		R15	2007-000606	R-CHIP;240ohm,1%,1/10W,TP,1608	1	SA	
						R150	2007-000869	R-CHIP;4.7Kohm,1%,1/10W,TP,1608	1	SNA	
P1	1404-001328	THERMISTOR-NTC;10Kohm,0A,3370K,0mW/	1	SNA							
PCB	AK41-00929A	PCB MAIN;BD-C5500,FR-4,4,00,1.2T,15	1	SNA		R151	2007-001007	R-CHIP;51Kohm,1%,1/10W,TP,1608	1	SA	
Q10	0501-000457	TR-SMALL SIGNAL;MMBT2222A/KST2222A,	1	SA		R152	2007-001292	R-CHIP;33ohm,5%,1/16W,TP,1005	1	SNA	
Q11	0501-000465	TR-SMALL SIGNAL;MMBT3904,NPN,350mW,	1	SA		R153	2007-001292	R-CHIP;33ohm,5%,1/16W,TP,1005	1	SNA	
Q12	0501-000465	TR-SMALL SIGNAL;MMBT3904,NPN,350mW,	1	SA		R154	2007-001292	R-CHIP;33ohm,5%,1/16W,TP,1005	1	SNA	

Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark	Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark
R155	2007-001292	R-CHIP,33ohm,5%,1/16W,TP,1005	1	SNA		R260	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R156	2007-001292	R-CHIP,33ohm,5%,1/16W,TP,1005	1	SNA		R261	2007-001044	R-CHIP,56ohm,5%,1/10W,TP,1608	1	SA	
R157	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R262	2007-001044	R-CHIP,56ohm,5%,1/10W,TP,1608	1	SA	
R158	2007-001292	R-CHIP,33ohm,5%,1/16W,TP,1005	1	SNA		R263	2007-000140	R-CHIP,1Kohm,5%,1/16W,TP,1005	1	SNA	
R159	2007-007651	R-CHIP,9.1Kohm,1%,1/10W,TP,1608	1	SA		R264	2007-000835	R-CHIP,39ohm,1%,1/10W,TP,1608	1	SA	
R16	2007-000606	R-CHIP,240ohm,1%,1/10W,TP,1608	1	SA		R265	2007-000835	R-CHIP,39ohm,1%,1/10W,TP,1608	1	SA	
R160	2007-000143	R-CHIP,4.7Kohm,5%,1/16W,TP,1005	1	SNA		R266	2007-000140	R-CHIP,1Kohm,5%,1/16W,TP,1005	1	SNA	
R161	2007-000141	R-CHIP,2.2Kohm,5%,1/16W,TP,1005	1	SNA		R267	2007-000170	R-CHIP,1Mohm,5%,1/16W,TP,1005	1	SNA	
R163	2007-000092	R-CHIP,15Kohm,5%,1/10W,TP,1608	1	SA		R269	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R164	2007-000141	R-CHIP,2.2Kohm,5%,1/16W,TP,1005	1	SNA		R27	2007-008015	R-CHIP,75ohm,1%,1/16W,TP,1005	1	SNA	
R165	2007-000096	R-CHIP,30Kohm,5%,1/10W,TP,1608	1	SA		R270	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R169	2007-001101	R-CHIP,62ohm,5%,1/10W,TP,1608	1	SA		R271	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R17	2007-000608	R-CHIP,240ohm,5%,1/10W,TP,1608	1	SA		R272	2007-001044	R-CHIP,56ohm,5%,1/10W,TP,1608	1	SA	
R170	2007-000140	R-CHIP,1Kohm,5%,1/16W,TP,1005	1	SNA		R273	2007-001044	R-CHIP,56ohm,5%,1/10W,TP,1608	1	SA	
R171	2007-000140	R-CHIP,1Kohm,5%,1/16W,TP,1005	1	SNA		R274	2007-001313	R-CHIP,330ohm,5%,1/16W,TP,1005	1	SNA	
R173	2007-000170	R-CHIP,1Mohm,5%,1/16W,TP,1005	1	SNA		R276	2007-000143	R-CHIP,4.7Kohm,5%,1/16W,TP,1005	1	SNA	
R176	2007-000159	R-CHIP,56Kohm,5%,1/16W,TP,1005	1	SNA		R277	2007-007313	R-CHIP,6.8Kohm,1%,1/16W,TP,1005	1	SA	
R178	2007-000979	R-CHIP,5.6Kohm,1%,1/10W,TP,1608	1	SA		R279	2007-000141	R-CHIP,2.2Kohm,5%,1/16W,TP,1005	1	SNA	
R179	2007-000140	R-CHIP,1Kohm,5%,1/16W,TP,1005	1	SNA		R28	2007-008015	R-CHIP,75ohm,1%,1/16W,TP,1005	1	SNA	
R18	2007-000657	R-CHIP,27ohm,1%,1/10W,TP,1608	1	SA		R280	2007-001325	R-CHIP,3.3Kohm,5%,1/16W,TP,1005	1	SNA	
R181	2007-000772	R-CHIP,33Kohm,1%,1/10W,TP,1608	1	SA		R281	2007-000162	R-CHIP,100Kohm,5%,1/16W,TP,1005	1	SNA	
R183	2007-001101	R-CHIP,62ohm,5%,1/10W,TP,1608	1	SA		R286	2007-000146	R-CHIP,6.8Kohm,5%,1/16W,TP,1005	1	SNA	
R184	2007-000869	R-CHIP,4.7Kohm,1%,1/10W,TP,1608	1	SNA		R288	2007-000141	R-CHIP,2.2Kohm,5%,1/16W,TP,1005	1	SNA	
R185	2007-000170	R-CHIP,1Mohm,5%,1/16W,TP,1005	1	SNA		R289	2007-007334	R-CHIP,200Kohm,1%,1/16W,TP,1005	1	SNA	
R186	2007-000162	R-CHIP,100Kohm,5%,1/16W,TP,1005	1	SNA		R29	2007-008015	R-CHIP,75ohm,1%,1/16W,TP,1005	1	SNA	
R188	2007-000570	R-CHIP,220ohm,1%,1/10W,TP,1608	1	SA		R290	2007-000157	R-CHIP,47Kohm,5%,1/16W,TP,1005	1	SNA	
R19	2007-000108	R-CHIP,510Kohm,5%,1/10W,TP,1608	1	SA		R291	2007-008339	R-CHIP,30Kohm,0.5%,1/16W,TP,1005	1	SNA	
R191	2007-000052	R-CHIP,10Kohm,1%,1/10W,TP,1608	1	SNA		R292	2007-000138	R-CHIP,100ohm,5%,1/16W,TP,1005	1	SNA	
R198	2007-000138	R-CHIP,100ohm,5%,1/16W,TP,1005	1	SNA		R293	2007-000157	R-CHIP,47Kohm,5%,1/16W,TP,1005	1	SNA	
R199	2007-000138	R-CHIP,100ohm,5%,1/16W,TP,1005	1	SNA		R294	2007-000140	R-CHIP,1Kohm,5%,1/16W,TP,1005	1	SNA	
R2	2007-002915	R-CHIP,4.02Kohm,1%,1/10W,TP,1608	1	SA		R295	2007-000695	R-CHIP,3.3ohm,5%,1/10W,TP,1608	1	SNA	
R20	2007-000999	R-CHIP,510ohm,1%,1/10W,TP,1608	1	SA		R296	2007-000695	R-CHIP,3.3ohm,5%,1/10W,TP,1608	1	SNA	
R200	2007-000137	R-CHIP,2Kohm,5%,1/16W,TP,1005	1	SNA		R297	2007-000695	R-CHIP,3.3ohm,5%,1/10W,TP,1608	1	SNA	
R201	2007-000138	R-CHIP,100ohm,5%,1/16W,TP,1005	1	SNA		R298	2007-007142	R-CHIP,10Kohm,1%,1/16W,TP,1005	1	SNA	
R203	2007-000152	R-CHIP,20Kohm,5%,1/16W,TP,1005	1	SNA		R299	2007-000695	R-CHIP,3.3ohm,5%,1/10W,TP,1608	1	SNA	
R204	2007-000152	R-CHIP,20Kohm,5%,1/16W,TP,1005	1	SNA		R3	2007-008453	R-CHIP,1.24Kohm,1%,1/16W,TP,1005	1	SNA	
R205	2007-000152	R-CHIP,20Kohm,5%,1/16W,TP,1005	1	SNA		R30	2007-008015	R-CHIP,75ohm,1%,1/16W,TP,1005	1	SNA	
R206	2007-000152	R-CHIP,20Kohm,5%,1/16W,TP,1005	1	SNA		R300	2007-000151	R-CHIP,15Kohm,5%,1/16W,TP,1005	1	SNA	
R208	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R301	2007-000695	R-CHIP,3.3ohm,5%,1/10W,TP,1608	1	SNA	
R209	2007-000152	R-CHIP,20Kohm,5%,1/16W,TP,1005	1	SNA		R302	2007-000503	R-CHIP,2.2ohm,5%,1/10W,TP,1608	1	SA	
R21	2007-000143	R-CHIP,4.7Kohm,5%,1/16W,TP,1005	1	SNA		R303	2007-000151	R-CHIP,15Kohm,5%,1/16W,TP,1005	1	SNA	
R210	2007-000140	R-CHIP,1Kohm,5%,1/16W,TP,1005	1	SNA		R304	2007-000503	R-CHIP,2.2ohm,5%,1/10W,TP,1608	1	SA	
R211	2007-001101	R-CHIP,62ohm,5%,1/10W,TP,1608	1	SA		R305	2007-000695	R-CHIP,3.3ohm,5%,1/10W,TP,1608	1	SNA	
R212	2007-000152	R-CHIP,20Kohm,5%,1/16W,TP,1005	1	SNA		R306	2007-000503	R-CHIP,2.2ohm,5%,1/10W,TP,1608	1	SA	
R216	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R307	2007-000151	R-CHIP,15Kohm,5%,1/16W,TP,1005	1	SNA	
R218	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R308	2007-000695	R-CHIP,3.3ohm,5%,1/10W,TP,1608	1	SNA	
R219	2007-000100	R-CHIP,68Kohm,5%,1/10W,TP,1608	1	SNA		R309	2007-001325	R-CHIP,3.3Kohm,5%,1/16W,TP,1005	1	SNA	
R22	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R31	2007-008015	R-CHIP,75ohm,1%,1/16W,TP,1005	1	SNA	
R222	2007-000152	R-CHIP,20Kohm,5%,1/16W,TP,1005	1	SNA		R310	2007-000695	R-CHIP,3.3ohm,5%,1/10W,TP,1608	1	SNA	
R223	2007-000152	R-CHIP,20Kohm,5%,1/16W,TP,1005	1	SNA		R311	2007-000695	R-CHIP,3.3ohm,5%,1/10W,TP,1608	1	SNA	
R23	2007-000570	R-CHIP,220ohm,1%,1/10W,TP,1608	1	SA		R312	2007-001325	R-CHIP,3.3Kohm,5%,1/16W,TP,1005	1	SNA	
R230	3301-002039	BEAD-SMD;26ohm,1608,TP	1	SA		R313	2007-001325	R-CHIP,3.3Kohm,5%,1/16W,TP,1005	1	SNA	
R232	2007-000152	R-CHIP,20Kohm,5%,1/16W,TP,1005	1	SNA		R314	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R233	2007-007318	R-CHIP,1Kohm,1%,1/16W,TP,1005	1	SNA		R315	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R235	2007-000939	R-CHIP,47Kohm,1%,1/10W,TP,1608	1	SA		R316	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R24	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R317	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R244	2007-000962	R-CHIP,5.1Kohm,1%,1/10W,TP,1608	1	SA		R32	2007-008015	R-CHIP,75ohm,1%,1/16W,TP,1005	1	SNA	
R25	2007-008015	R-CHIP,75ohm,1%,1/16W,TP,1005	1	SNA		R320	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R254	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R322	2007-000157	R-CHIP,47Kohm,5%,1/16W,TP,1005	1	SNA	
R255	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R323	2007-000157	R-CHIP,47Kohm,5%,1/16W,TP,1005	1	SNA	
R256	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R325	2007-000138	R-CHIP,100ohm,5%,1/16W,TP,1005	1	SNA	
R259	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA		R328	2007-000148	R-CHIP,10Kohm,5%,1/16W,TP,1005	1	SNA	
R26	2007-008015	R-CHIP,75ohm,1%,1/16W,TP,1005	1	SNA		R33	2007-008015	R-CHIP,75ohm,1%,1/16W,TP,1005	1	SNA	

Exploded Views and Parts List

Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark	Loc.No	Parts No	Description / Specification	Qty	S.N.A	Remark
TR8	2007-000152	R-CHIP;20Kohm,5%,1/16W,TP,1005	1	SNA		0103-005096	RESIN-ABS;HB,ABS+PMMA	25	SNA		
TR9	2007-003012	R-CHIP;2.2Mohm,5%,1/16W,TP,1005	1	SNA		0103-007279	RESIN-PMMA;TP0010,HB,PMMA,PMMA(Clea	15	SNA		
	AK97-04159A	ASSY SMD-TOUCH;AK94-00281D	1	SNA		0103-007279	RESIN-PMMA;TP0010,HB,PMMA,PMMA(Clea	15	SNA		
REMO2AK59-00104R	REMOCON-ASSY;"10 BDP BD-C5500/XAA,S	1 SA				AA63-01386A	GASKET-EMI,SPONGE;SP-P300M,Conducti	1	SNA		
	AK83-01054A	CKD-TM1052;CASE-TOP,ABS+PMMA,SF-050	1	SNA		AK61-01001A	HOLDER-TOUCH;BD-C5300/XAA,ABS,T2,43	1	SNA		
	AK83-01055A	CKD-TM1052;CASE-BOTTOM,ABS,HF-0680,	1	SNA		AK63-00637A	SHEET-FUNCTION;BD-C5300/XAA,PET,T0.1	1	SNA		
	AK83-01056A	CKD-TM1052;DOOR-BATTERY,ABS,HF-0680	1	SNA		AK63-00684A	SHEET-HOLDER TOUCH;BD-C5300,FELT,0.	1	SNA		
	AK83-01057A	CKD-TM1052;KNOB-ENTER,ABS,HF-0680,2	1	SNA		AK64-02439A	DECO PANEL-L;BD-C5300/XAA,PMMA,T2,1	1	SNA		
	AK83-01058A	CKD-TM1052;KNOB-NAVIGATION,ABS,HF-0	1	SNA		AK64-02440A	DECO PANEL-R;BD-C5300/XAA,PMMA,T2.1	1	SNA		
	AK83-01059A	CKD-TM1052;HOLDER-WIRE,URETHANE(ELA	1	SNA		AK68-01941R	MANUAL USERS;BD-C5300,XEN,ENG,FR,DE	1	SNA		
	AK83-01060A	CKD-TM1052;RUBBER-KEY,SILICONE/ ECR	1	SNA		6801-001763	CARD-REGISTRATION;Europe Registrati	1	SNA		
	AK83-01061A	CKD-TM1052;SPRING-REMOCON(+),SUS 30	1	SNA		AK97-02206A	ASSY BAG-PE;BAG PE,HT-X20R,HT-X20R,	1	SNA		
	AK83-01062A	CKD-TM1052;SPRING-REMOCON(-),SUS 30	1	SNA		AK94-00333A	ASSY PCB SMPS-SKD;BD-C5500/XER,BD-C	1	SNA		
	AK83-01063A	CKD-TM1052;SPRING-REMOCON(C),SUS 30	1	SNA		AK68-01955E	LABEL-POP STAND;BD-C5300/XEF,SEF,AR	1	SNA		
	AK83-01064A	CKD-TM1052;FOAM-BAG,SUS 304 0.5	1	SNA		AK69-00821B	BOX-SET;BD-C5300/XEF,CB,SW2,A-1,O	1	SNA		
	AK83-01065A	CKD-TM1052;PASSE-LABEL,ART PAPER(12	1	SNA		6902-000604	BAG WRAPPING;LDPE,T0.02,W500,L10000	0.9	SNA		
	AK83-01066A	CKD-TM1052;PCB-REMOCON,XPC-1,44*203	1	SNA		AK63-00435B	SHEET-NITRON;BD-C5300/XAA,NITRON,0.	1	SNA		
	AK83-01067A	CKD-TM1052;R-CHIP,0,J,1/8W,1608,SMD	1	SNA		BN69-00257B	PACKING-PAD;PAPER,CB-SW4,1130,820,Y	0.03	SNA		
	AK83-01068A	CKD-TM1052;TANTALUM,47uF,M,6.3V,A S	1	SNA		BN69-03982F	PAD PACKING-EDGE;LB6T,PAPER,8,120,2	0.024	SNA		
	AK83-01069A	CKD-TM1052;C-CHIP,104,Z,50V,1608,Y5	1	SNA		BN69-04822Y	PALLET;-WOOD,1050,1150,135,8500,20	0.006	SNA		
	AK83-01070A	CKD-TM1052;TACT SW,KTS-1102F,DHT-1	1	SNA		AK90-00071J	ASSY COVER BOTTOM;BD-C5300	1	SNA		
	AK83-01071A	CKD-TM1052;LED-IR,SIS411-HISB5010IR	1	SNA		AK90-00080A	ASSY DECK-SKD;BD-C5500,SEIN,BD-P6A,	1	SNA		
	AK83-01072A	CKD-TM1052;IC-MCU,*ADAM41P2723G,SOP	1	SNA		AK90-00083A	ASSY COVER FRONT;BD-C5300/XEF	1	SNA		
ACCE1	AK92-01948B	ASSY ACCESSORY;BD-C5300/EDC	1	SNA		AK91-01042A	ASSY SHIELD;BD-C5300/XEF,ASSY SHIEL	1	SNA		
AS095	AK63-00654E	SHEET-PCB;BD-C6900/XAA,PET,T0.2,W55	1	SNA		AK92-01949A	ASSY LABEL;BD-C5300/XEF	1	SNA		
B001A	AK96-01281L	ASSY COVER P-BOTTOM;BD-C5300/XEF,FR	1	SNA		AK92-01964A	ASSY BOX;BD-C5300/XEF	1	SNA		
C- AV	AC39-42001R	CABLE-AV;PVC	1	SC		AK92-01965A	ASSY P/MATERIAL;BD-C5300/XEF	1	SNA		
C011	AK61-00137A	SPRING ETC-DOOR;DVD-R4000,COIL,PI0.	1	SA							
C1023	AK61-00608A	LEG;DVD-VR330,RUBBER,BLK,12	2	SNA							
CC02	AK64-02428L	CHASSIS-BOTTOM;BD-C5300/XEF,EGI-SEC	1	SNA							
CCM1	BN63-05199B	COVER-SHEET;AMBER,PE,T0.08,W65mm,20	0.45	SNA							
CCM1	AK68-01466Y	LABEL RATING;BD-P1600A/XER,SER,PET,	1	SNA							
CIS1	0203-001586	TAPE-FILAMENT;#893,0.15,25,55	0.05	SNA							
CLAMPE	AK65-00001A	CLAMPER CORE-CORD POWER;EXINO,ABS 9	1	SNA							
D001A	AK96-01294A	ASSY ENGINE P-BD DECK;BD-P6A,SEIN,1	1	SA							
F001	AK64-02436A	PANEL-FRONT;BD-C5300/XAA,PC,T2.5,W4	1	SNA							
F001A	AK96-01282A	ASSY COVER P-FRONT;BD-C5300/XEF,SEF	1	SA							
FD03	AK64-02438A	DOOR-TRAY;BD-C5300/XAA,PMMA + ABS H	1	SA							
FD12	AK64-02427A	DOOR-USB;BD-C5500/XAA,ABS BLK + ELA	1	SA							
FW05	AK64-02437A	WINDOW-VFD;BD-C5300/XEF,PMMA+ABS HB	1	SNA							
L-BARC	AH68-00371A	LABEL-BAR CODE;ALL,ALL,ART PAPER,0.	1	SNA							
M0017	AK91-01041A	ASSY CHASSIS;BD-C5300/XEF,ASSY CHAS	1	SNA							
M0045	AK97-01943A	ASSY ACCESSORY;DVD-R157/XAA,-,NEXUS	1	SNA							
S.N.A	4301-001035	BATTERY-ALKALINE;1.5V,0mAh,LR03,10.	2	SNA							
S.N.A	0203-001100	TAPE-OPP MASKING;OPP/W75/CLR,T0.075	1.292	SNA							
T001	AK63-00607B	COVER-TOP;BD-C5300/XEF,PCM,T0.45,W5	1	SA							
T0246	AK69-00801A	CUSHION-SET;BD-C5500,EPS,WHITE,16.7	1	SNA							
T0268	AC39-10019A	CBF-POWER CORD;AT,CP2,HOUIING(2P),25	1	SA							
T0524	6902-000286	BAG PE;LDPE,T0.03,W200,L300,TRP,8,2	1	SNA							
UNIT7A	AK96-01049K	ASSY MANUAL P;BD-C5300,IB,QG,EDC	1	SNA							
UNIT7A	AK96-01408X	ASSY MANUAL P;BD-C5300,IB,CARD,EDC	1	SNA							
W275	6003-001561	SCREW-TAPTYPE;BH,+,B,M3,L6,ZPC(WH	4	SA							
W275	6003-001561	SCREW-TAPTYPE;BH,+,B,M3,L6,ZPC(WH	3	SA							
W275	6003-001561	SCREW-TAPTYPE;BH,+,B,M3,L6,ZPC(WH	4	SA							
W390	6003-000276	SCREW-TAPTYPE;BH,+,B,M3,L10,ZPC(W	3	SA							
W391	6003-000275	SCREW-TAPTYPE;BH,+,B,M3,L10,ZPC(BLK	1	SA							
W391	6003-000275	SCREW-TAPTYPE;BH,+,B,M3,L10,ZPC(BLK	3	SA							
	0103-004618	RESIN-ABS;WT0034,HB,ABS,High Flow A	16	SNA							
	0103-007304	RESIN-PMMA;BK0041,UL-94 HB,PMMA+ABS	100	SNA							
	0103-007304	RESIN-PMMA;BK0041,UL-94 HB,PMMA+ABS	15	SNA							

MEMO